

Brake cylinder: Double acting, single rod/double acting, no-lubrication

JSC3/JSC4-N Series

● Bore size:
JSC3: ø40/ø50/ø63/ø80/ø100
JSC4: ø125/ø140/ø160/ø180

JIS symbol



RoHS CAD

Specifications

Item			JSC3 (with switch)					JSC3-S (with switch)					JSC4-N			
Bore size		mm	ø40	ø50	ø63	ø80	ø100	ø40	ø50	ø63	ø80	ø100	ø125	ø140	ø160	ø180
Actuation			Double acting					Double acting/low pressure release					Double acting			
Working fluid			Compressed air													
Max. working pressure		MPa	1.0 (≈150 psi, 10 bar)													
Min. working pressure	Brake section	MPa	0.3 (≈44 psi, 3 bar)					0.25 (≈36 psi, 2.5 bar)					0.3 (≈44 psi, 3 bar)			
	Cylinder	MPa	0.1 (≈15 psi, 1 bar)					0.1 (≈15 psi, 1 bar)					0.05 (≈7.3 psi, 0.5 bar)			
Proof pressure		MPa	1.6 (≈230 psi, 16 bar)													
Ambient temperature		°C	-10 (14°F) to 60 (140°F) (no freezing)					-10 (14°F) to 60 (140°F) (no freezing)					-5 (23°F) to 60 (140°F) (no freezing)			
Port size	Brake section		Rc1/8		Rc1/4		Rc3/8	Rc1/8		Rc1/4		Rc3/8	Rc1/2			
	Cylinder		Rc1/4	Rc3/8		Rc1/2		Rc1/4	Rc3/8		Rc1/2		Rc1/2	Rc3/4		
Stroke tolerance		mm	$^{+0.9}_{0}$ (to 360) $^{+1.4}_{0}$ (to 1000)					$^{+1.0}_{0}$ (to 360) $^{+1.4}_{0}$ (to 1000)					$^{+1.0}_{0}$ (to 300), $^{+1.4}_{0}$ (to 1000), $^{+1.8}_{0}$ (to 2000)			
Working piston speed		mm/s	50 to 1000 (Operate within the allowable absorbed energy.)													
Cushion			Air cushion													
Effective air cushion length		mm	14.6	16.6		20.6	23.6	14.6	16.6		20.6	23.6	21.6			
Lubrication			Not required (use turbine oil class 1 ISO VG32 if necessary for lubrication)													
Holding force		N	980	1569	2451	3922	6178	784	1255	1961	3138	4941	9600	12000	15800	20000
Allowable absorbed energy	Cushioned	J	4.29	8.37	15.8	27.9	49.8	4.29	8.37	15.8	27.9	49.8	63.6	91.5	116	152
	Without cushion	J	0.067	0.079	0.079	0.201	0.301	0.067	0.079	0.079	0.201	0.301	0.371	0.386	0.386	0.958
			Note: Without any cushion, this product cannot absorb large energy generated by an external load. We recommend using an external shock absorber.													

Stroke

Bore size (mm)		Standard stroke (mm)	Max. stroke (mm)	Available stroke (mm)	Min. stroke (mm)
JSC3	ø40	50, 75, 100, 150, 200, 250, 300, 350, 400, 450, 500	600	1600	1
	ø50			2000	
	ø63			2500 *2	
	ø80		700		
	ø100		800		
JSC4	ø125	50, 75, 100, 150, 200, 250, 300	800	2000	
	ø140				
	ø160				
	ø180		900		

*1 : If the max. stroke is exceeded, product specifications may not be met, depending on operating conditions. Refer to Ending Page 69 for details.
The custom stroke is available in 1 mm increments.
*2 : The max. stroke available for ø63 to ø100 bore size models with bellows is 2000 mm.

Min. stroke with switch (T switch)

● Min. stroke with T0/T5 switches

Switch quantity	Different surface mounting				Same surface mounting				Center trunnion mounting				Rod side trunnion mounting Position cannot be detected at the rod side stroke end.	Head side trunnion mounting No position detection at head side stroke end.
Bore size	1	2	3	4	1	2	3	4	1	2	3	4	1	1
ø40	20(10)	20(20)	40(40)	60(60)	20(10)	60(45)	105(75)	150(105)	110(110)	110(110)	175(145)	175(145)	50(50)	50(50)
ø50	15(10)	20(20)	40(40)	60(60)	15(10)	20(20)	65(50)	65(60)	135(135)	135(135)	135(135)	135(135)	60(60)	60(60)
ø63	15(10)	20(20)	40(40)	60(60)	15(10)	20(20)	70(55)	70(60)	110(95)	110(95)	110(100)	110(100)	50(45)	50(45)
ø80	15(15)	25(25)	45(45)	65(65)	15(15)	25(25)	70(55)	70(65)	115(85)	115(85)	115(105)	115(105)	55(40)	55(40)
ø100	15(15)	25(25)	45(45)	70(70)	15(15)	25(25)	70(55)	70(70)	125(95)	125(95)	125(115)	125(115)	60(45)	60(45)

*1 : The values in ( ) are of T*V (radial lead wire).
*2 : When the stroke is 15 mm or less, the two switches could turn ON at the same time. In this case, adjust switch mounting positions to be as far apart as possible.

Min. stroke with JSC3 switch (T switch)

● T8 min. stroke with switch

Switch quantity	Different surface mounting				Same surface mounting				Center trunnion mounting				Rod side trunnion mounting Position cannot be detected at the rod side stroke end.	Head side trunnion mounting No position detection at head side stroke end.
Bore size	1	2	3	4	1	2	3	4	1	2	3	4	1	1
ø40	15(10)	20(20)	40(40)	60(60)	15(10)	50(35)	95(65)	140(95)	95(85)	95(85)	155(125)	155(125)	45(40)	45(40)
ø50	10(10)	20(20)	40(40)	60(60)	10(10)	20(20)	70(55)	70(60)	115(115)	115(115)	135(135)	135(135)	50(50)	50(50)
ø63	10(10)	20(20)	40(40)	60(60)	10(10)	20(20)	70(55)	70(60)	95(75)	95(75)	110(110)	110(110)	45(35)	45(35)
ø80	15(15)	25(25)	45(45)	65(65)	15(15)	25(25)	70(55)	70(65)	100(70)	100(70)	115(115)	115(115)	50(35)	50(35)
ø100	15(15)	25(25)	45(45)	65(65)	15(15)	25(25)	70(55)	70(65)	110(80)	110(80)	125(125)	125(125)	55(40)	55(40)

*1: The values in ( ) are of T*V (radial lead wire).
*2: When the stroke is 15 mm or less, the two switches could turn ON at the same time. In this case, adjust switch mounting positions to be as far apart as possible.

● Min. stroke with T2/T3 switches

Switch quantity	Different surface mounting				Same surface mounting				Center trunnion mounting				Rod side trunnion mounting Position cannot be detected at the rod side stroke end.	Head side trunnion mounting No position detection at head side stroke end.
Bore size	1	2	3	4	1	2	3	4	1	2	3	4	1	1
ø40	20(10)	20(15)	25(25)	40(40)	20(10)	60(45)	105(75)	150(105)	105(75)	105(75)	165(135)	165(135)	50(35)	50(35)
ø50	15(10)	15(15)	25(25)	40(40)	15(10)	15(15)	60(45)	60(45)	105(75)	105(75)	105(75)	105(75)	45(30)	45(30)
ø63	15(10)	15(15)	25(25)	40(40)	15(10)	15(15)	60(45)	60(45)	110(80)	110(80)	110(85)	110(85)	50(35)	50(35)
ø80	15(10)	15(15)	30(30)	45(45)	15(10)	15(15)	60(45)	60(45)	115(85)	115(85)	115(90)	115(90)	55(40)	55(40)
ø100	10(10)	15(15)	30(30)	45(45)	10(10)	15(15)	60(45)	60(45)	125(95)	125(95)	125(100)	125(100)	60(45)	60(45)

*1: The values in ( ) are of T*V (radial lead wire).
*2: When the stroke is 15 mm or less, the two switches could turn ON at the same time. In this case, adjust switch mounting positions to be as far apart as possible.

● Min. stroke with T1/T2Y/T3Y/T2YD switches

	Different surface mounting				Same surface mounting				Center trunnion mounting				Rod side trunnion mounting Position cannot be detected at the rod side stroke end.	Head side trunnion mounting No position detection at head side stroke end.
Switch quantity	1	2	3	4	1	2	3	4	1	2	3	4	1	1
ø40	20(10)	20(15)	25(25)	40(40)	20(10)	60(45)	105(75)	150(105)	105(75)	105(75)	165(135)	165(135)	50(35)	50(35)
ø50	15(10)	15(15)	25(25)	40(40)	15(10)	15(15)	60(45)	60(45)	100(70)	100(70)	100(75)	100(75)	45(30)	45(30)
ø63	15(10)	15(15)	25(25)	40(40)	15(10)	15(15)	60(45)	60(45)	105(75)	105(75)	105(85)	105(85)	50(35)	50(35)
ø80	15(10)	15(15)	30(30)	45(45)	15(10)	15(15)	60(45)	60(45)	110(80)	110(80)	110(90)	110(90)	55(40)	55(40)
ø100	10(10)	15(15)	30(30)	45(45)	10(10)	15(15)	60(45)	60(45)	120(90)	120(90)	120(100)	120(100)	60(45)	60(45)

*1: The values in ( ) are of T*V (radial lead wire). T2YD does not have a radial lead wire (V).
*2: When the stroke is 15 mm or less, the two switches could turn ON at the same time. In this case, adjust switch mounting positions to be as far apart as possible.

● Min. stroke with T2W/T3W switches

	Different surface mounting				Same surface mounting				Center trunnion mounting				Rod side trunnion mounting Position cannot be detected at the rod side stroke end.	Head side trunnion mounting No position detection at head side stroke end.
Switch quantity	1	2	3	4	1	2	3	4	1	2	3	4	1	1
ø40	20(5)	20(10)	20(15)	25(25)	20(5)	65(50)	110(80)	155(110)	110(80)	110(80)	170(140)	170(140)	50(35)	50(35)
ø50	20(5)	20(10)	20(15)	20(20)	20(5)	20(10)	65(40)	65(40)	110(80)	110(80)	110(60)	110(60)	50(35)	50(35)
ø63	20(5)	20(10)	20(15)	25(25)	20(5)	20(10)	65(40)	65(40)	115(85)	115(85)	115(65)	115(65)	55(40)	55(40)
ø80	15(5)	15(10)	15(15)	25(25)	15(5)	15(10)	60(40)	60(40)	120(90)	120(90)	120(70)	120(70)	55(40)	55(40)
ø100	10(5)	10(10)	20(20)	25(25)	10(5)	10(10)	60(40)	60(40)	130(100)	130(100)	130(85)	130(85)	60(45)	60(45)

*1: The values in ( ) are of T*V (radial lead wire).
*2: When the stroke is 15 mm or less, the two switches could turn ON at the same time. In this case, adjust switch mounting positions to be as far apart as possible.

Min. stroke with JSC4 switch (T switch)

● ø125 to ø180

(Unit: mm)

Item / Bore size (mm)	Stroke when mounted on the same surface	Center trunnion mounting stroke	Rod side trunnion mounting stroke	Head side trunnion mounting stroke
				
ø125	20 or more	120 or more	70 or more	
ø140		125 or more	75 or more	
ø160		130 or more	80 or more	
ø180		135 or more	85 or more	

Switch specifications (T type switch)

● 1-color/2-color LED/for AC magnetic field proof

Item	Proximity 2-wire	Proximity 2-wire			Proximity 3-wire				Reed 2-wire						Proximity 2-wire
	T1H/ T1V	T2H/T2V/ T2JH/T2JV	T2YH/ T2YV	T2WH/ T2WV	T3H/ T3V	T3PH/ T3PV	T3YH/ T3YV	T3WH/ T3WV	T0H/T0V		T5H/T5V		T8H/T8V		T2YD(*4) T2YDT
Applications	For programmable controller, relay, compact solenoid valve	Dedicated for programmable controller			For programmable controller, relay				For programmable controller, relay		For programmable controller, relay, IC circuit (no indicator lamp), serial connection		For programmable controller, relay		For programmable controller
Output method	-				NPN output	PNP output	NPN output	NPN output	-						
Pwr. supp. V.	-				10 to 28 VDC				-						
Load voltage	85 to 265 VAC	10 to 30 VDC		24 VDC ±10%	30 VDC or less				12/24 VDC	110 VAC	5/12/24 VDC	110 VAC	12/24 VDC	110 VAC	220 VAC	24 VDC ±10%
Load current	5 to 100 mA	5 to 20 mA (*3)			100 mA or less		50 mA or less		5 to 50 mA	7 to 20 mA	≤50 mA	≤20 mA	5 to 50 mA	7 to 20 mA	7 to 10 mA	5 to 20 mA
Indicator lamp	LED (Lit when ON)	LED (Lit when ON)	Red/green LED (Lit when ON)	Red/green LED (Lit when ON)	LED (Lit when ON)	Yellow LED (Lit when ON)	Red/green LED (Lit when ON)	Red/green LED (Lit when ON)	LED (Lit when ON)		Without LED		LED (Lit when ON)			Red/green LED (Lit when ON)
Leakage current	≤1 mA at 100 VAC, ≤2 mA at 200 VAC	1 mA or less			10 μA or less				0 mA							1 mA or less
Weight g	1 m:33 3 m:87 5 m:142	1 m:18 3 m:49 5 m:80	1 m:33 3 m:87 5 m:142	1 m:18 3 m:49 5 m:80	1 m:18 3 m:49 5 m:80		1 m:33 3 m:87 5 m:142	1 m:18 3 m:49 5 m:80	1 m:18 3 m:49 5 m:80				1 m:33 3 m:87 5 m:142			1 m:61 3 m:166 5 m:272

*1 : Refer to Ending Page 1 for detailed switch specifications and dimensions.
*2 : Switches other than the above models, such as switches with connectors, are also available. Refer to Ending Page 1.
*3 : The max. load current is 20 mA at 25°C. The current is lower than 20 mA if the operating ambient temperature around the switch is higher than 25°C. (5 to 10 mA at 60°C)
*4 : AC magnetic field proof switch (T2YD/T2YDT) cannot be used in DC magnetic fields.